

# AP Series Battery Charge and Run Time Information



## Battery Charging Times (Minutes for 80% / 100% Charge)

Tool Model	AP 100	AP 100	AP 300	NEW! AP 300S	AR 1000	AR 2000	AR 3000
AL 101	60 / 90	75 / 100	190 / 250	230 / 300	X	X	X
AL 300	25 / 35	30 / 45	45 / 65	55 / 70	130 / 160	190 / 215	220 / 265
AL 500	25 / 35	30 / 45	25 / 35	30 / 45	90 / 120	100 / 130	120 / 160

## Working Times Per Battery Charge<sup>1</sup> (Minutes)

Tool Model	AP	AP	AP	AP	AP	AP	AP
MSA 160 C-BQ	17	18	<b>50</b>	62	125	180	230
MSA 200 C-BQ	15	18	<b>45</b>	56	110	160	200
HTA 65	17	18	<b>55</b>	68	125	180	230
HTA 85	17	18	<b>55</b>	68	125	180	230
KMA 130 R <sup>2</sup> (FS-KM head)	13 / 8 / 6	16 / 7	35 / 22 / 18	47 / 22	100 / 60 / 50	140 / 90 / 75	<b>180 / 110 / 90</b>
FSA 85	15	18	<b>45</b>	56	120	160	200
FSA 90 R (nylon head)	10	12	<b>30</b>	37	80	120	150
FSA 130 R <sup>2</sup> (nylon head)	16 / 12 / 8	19 / 10	40 / 30 / 20	50 / 25	100 / 85 / 70	<b>150 / 120 / 100</b>	190 / 150 / 125
HSA 66	<b>60</b>	<b>72</b>	180	223	450	660	800
HSA 94 R <sup>2</sup>	45 / 40 / 35	54 / 42	135 / 120 / 105	167 / 130	<b>380 / 350 / 320</b>	550 / 500 / 450	700 / 630 / 570
HSA 94 T <sup>2</sup>	45 / 40 / 35	54 / 42	135 / 120 / 105	167 / 130	<b>380 / 350 / 320</b>	550 / 500 / 450	700 / 630 / 570
HLA 65	<b>60</b>	<b>72</b>	180	223	450	660	800
HLA 85	<b>60</b>	<b>72</b>	180	223	450	660	800
BGA 85	7	10	<b>24</b>	30	65	90	115
BGA 100 <sup>3</sup>	27 / 11 / 7 / 7	32 / 8	83 / 33 / 21 / 16	103 / 20	225 / 95 / 60 / 45	300 / 130 / 80 / 60	<b>395 / 160 / 100 / 75</b>
TSA 230	6	7	<b>18</b>	22	X	X	X

## Working Ranges per Battery Charge<sup>3</sup> (Sq. Ft.)

Tool Model	AP	AP	AP	AP	AP	AP	AP
RMA 370	1,500	X	4,000	X	X	X	X
RMA 410C	1,600	X	4,300	X	X	X	X
RMA 510	X	X	5,100	-	X	X	X

Recommended battery Reduced tool performance X Not Applicable

<sup>1</sup> The battery working times and area specifications for each battery charge are estimates and may vary depending on application.

<sup>2</sup> Level 1 / level 2 / level 3

<sup>3</sup> Level 1 / level 2 / level 3 / Boost

# AP Series Battery Charge and Run Time Information

	AP 100	AP 300	AR 1000	AR 2000	AR 3000
<b>KMA 130 R Attachment Working Times Per Battery Charge<sup>1</sup> (Minutes) – Performance Levels 1 / 2 / 3</b>					
<b>BF – KM</b> Mini-Cultivator	15 / 13 / 12	45 / 40 / 35	125 / 110 / 90	180 / 155 / 140	230 / 190 / 180
<b>BG – KM</b> Blower	13 / 7 / 5	35 / 20 / 13	100 / 60 / 40	150 / 85 / 60	190 / 110 / 70
<b>FBD – KM</b> Bed Redefiner	5 / 5 / 5	15 / 15 / 15	40 / 40 / 40	55 / 55 / 55	70 / 70 / 70
<b>FCB – KM</b> Curved Lawn Edger	11 / 9 / 6	32 / 25 / 17	90 / 70 / 45	130 / 100 / 85	160 / 130 / 85
<b>FCS – KM</b> Straight Lawn Edger	11 / 9 / 6	32 / 25 / 17	90 / 70 / 45	130 / 100 / 70	160 / 130 / 85
<b>FS – KM</b> Brushcutter	25 / 18 / 15	75 / 55 / 45	200 / 150 / 130	300 / 220 / 190	380 / 270 / 240
<b>FS – KM</b> Line Head Trimmer	13 / 8 / 6	35 / 22 / 18	100 / 60 / 50	140 / 90 / 75	180 / 110 / 90
<b>FH – KM</b> 145° Power Scythe	60 / 50 / 40	180 / 145 / 120	500 / 400 / 330	730 / 580 / 480	900 / 730 / 600
<b>HL – KM</b> 0° Hedge Trimmer	60 / 50 / 40	180 / 145 / 120	500 / 400 / 330	730 / 580 / 480	900 / 730 / 600
<b>HL – KM</b> 145° Hedge Trimmer	60 / 50 / 40	180 / 145 / 120	500 / 400 / 330	730 / 580 / 480	900 / 730 / 600
<b>HT – KM</b> Pole Pruner	20 / 15 / 9	60 / 45 / 30	170 / 125 / 75	250 / 180 / 110	310 / 230 / 140
<b>KB – KM</b> Bristle Brush	15 / 13 / 12	45 / 40 / 35	125 / 110 / 90	180 / 155 / 140	230 / 190 / 180
<b>KW – KM</b> STIHL PowerSweep™	15 / 13 / 12	45 / 40 / 35	125 / 110 / 90	180 / 155 / 140	230 / 190 / 180

<sup>1</sup> The battery working times and area specifications for each battery charge are estimates and may vary depending on application.